



Technical Specification Product Engineering

Model AE4430Y-FZ1A	BM AE-8001-BR	Nominal Voltage (V)		Refrigerant R134a	Cooling Fan																																																												
		60 Hz -----	50 Hz 220-240																																																														
Basic Data																																																																	
<p>Operating Voltage Range(V) : 60 Hz: ----- 50 Hz: 198 - 253 Application : High Back Pressure (HBP) Evaporating Temperature Range : -15°C to +15°C (+5°F to +59°F) Motor Type : CSIR Starting Torque Class : High Start Torque (HST) Expansion Device : Capillary Tube or Expansion Valve Commercial Designation : 1/4 HP Oil Type : Polyol Ester Viscosity : 32 cSt@40°C Oil Charge : 280 ml Displacement : 8.02 cc/rev Net Weight : 9.4 Kg Approval : VDE/CE/CCC/GOST</p>																																																																	
Expected Performance																																																																	
<table border="0" style="width: 100%;"> <tr> <td style="width: 30%;">Test Condition :</td> <td colspan="4" style="text-align: center;">ASHRAE</td> </tr> <tr> <td>Test Voltage :</td> <td colspan="4">220V/50Hz</td> </tr> <tr> <td>Cooling Capacity (+/-5%) (BTU/h) :</td> <td colspan="4">2820</td> </tr> <tr> <td>(Kcal/h) :</td> <td colspan="4">711</td> </tr> <tr> <td>(W) :</td> <td colspan="4">827</td> </tr> <tr> <td>Rated Watts(+/-5%)(W) :</td> <td colspan="4">336</td> </tr> <tr> <td>Rated Current(+/-5%)(A) :</td> <td colspan="4">2.2</td> </tr> <tr> <td>Efficiency-EER(-9.04%/+10.5%)(BTU/Wh) :</td> <td colspan="4">8.39</td> </tr> <tr> <td>(Kcal/Wh) :</td> <td colspan="4">2.12</td> </tr> <tr> <td>(W/W) :</td> <td colspan="4">2.46</td> </tr> <tr> <td>LRA (Max.) (A) :</td> <td colspan="4">11.5</td> </tr> <tr> <td>Winding Resistance at 25°C (+/-7%)(ohm):</td> <td>Main: 8.58</td> <td>Start: 53.44</td> <td colspan="2"></td> </tr> </table>						Test Condition :	ASHRAE				Test Voltage :	220V/50Hz				Cooling Capacity (+/-5%) (BTU/h) :	2820				(Kcal/h) :	711				(W) :	827				Rated Watts(+/-5%)(W) :	336				Rated Current(+/-5%)(A) :	2.2				Efficiency-EER(-9.04%/+10.5%)(BTU/Wh) :	8.39				(Kcal/Wh) :	2.12				(W/W) :	2.46				LRA (Max.) (A) :	11.5				Winding Resistance at 25°C (+/-7%)(ohm):	Main: 8.58	Start: 53.44		
Test Condition :	ASHRAE																																																																
Test Voltage :	220V/50Hz																																																																
Cooling Capacity (+/-5%) (BTU/h) :	2820																																																																
(Kcal/h) :	711																																																																
(W) :	827																																																																
Rated Watts(+/-5%)(W) :	336																																																																
Rated Current(+/-5%)(A) :	2.2																																																																
Efficiency-EER(-9.04%/+10.5%)(BTU/Wh) :	8.39																																																																
(Kcal/Wh) :	2.12																																																																
(W/W) :	2.46																																																																
LRA (Max.) (A) :	11.5																																																																
Winding Resistance at 25°C (+/-7%)(ohm):	Main: 8.58	Start: 53.44																																																															
Electrical Components																																																																	
<table border="0" style="width: 100%;"> <tr> <td style="width: 50%; vertical-align: top;"> <p>Starting Relay : Sensata Code : -----</p> <p>Connection Type : Fast-on:--- Pick-up : ----- A Drop-out : ----- A</p> <p>Potential Relay : ELECTRICA Code : ----- Pick-up : --- V Drop-out : --- V</p> <p>Starting Relay - PTC : Sensata Code : ----- PTC-Resistance : --- Ohms Power Consumption of PTC : --- W</p> <p>Overload Protector : Sensata Code : ----- Connection Type : Fast-on:--- Disc Opening Temperature (+/-5°C) : --- °C Disc Closing Temperature (+/-9°C) : --- °C Time Check Current : --- A Time Check at 25°C : --- s Trip Current : --- A at --- °C</p> <p>Combo Module : Capacitor : Start: 47-56MFD 250VAC Connection Box : -----</p> <p>Note :</p> </td> <td style="width: 50%; vertical-align: top;"> <p style="text-align: center;">or</p> <p>COMPELA RP42XX</p> <p>Screw:--- Fast-on:38 Screw:--- 5.80 A 4.95 A</p> <p style="text-align: center;">or</p> <p>G.E. ----- ----- V ----- V</p> <p style="text-align: center;">or</p> <p>COMPELA ----- --- Ohms --- W</p> <p style="text-align: center;">or</p> <p>COMPELA T14526-XX</p> <p>Screw:--- Fast-on:23 Screw:24 120 °C 52 °C 8.00 A 6.5 - 16 s 2.50 A at 90 °C</p> <p style="text-align: center;">Run: ----- TPCo Process ----- 1009</p> </td> </tr> </table>						<p>Starting Relay : Sensata Code : -----</p> <p>Connection Type : Fast-on:--- Pick-up : ----- A Drop-out : ----- A</p> <p>Potential Relay : ELECTRICA Code : ----- Pick-up : --- V Drop-out : --- V</p> <p>Starting Relay - PTC : Sensata Code : ----- PTC-Resistance : --- Ohms Power Consumption of PTC : --- W</p> <p>Overload Protector : Sensata Code : ----- Connection Type : Fast-on:--- Disc Opening Temperature (+/-5°C) : --- °C Disc Closing Temperature (+/-9°C) : --- °C Time Check Current : --- A Time Check at 25°C : --- s Trip Current : --- A at --- °C</p> <p>Combo Module : Capacitor : Start: 47-56MFD 250VAC Connection Box : -----</p> <p>Note :</p>	<p style="text-align: center;">or</p> <p>COMPELA RP42XX</p> <p>Screw:--- Fast-on:38 Screw:--- 5.80 A 4.95 A</p> <p style="text-align: center;">or</p> <p>G.E. ----- ----- V ----- V</p> <p style="text-align: center;">or</p> <p>COMPELA ----- --- Ohms --- W</p> <p style="text-align: center;">or</p> <p>COMPELA T14526-XX</p> <p>Screw:--- Fast-on:23 Screw:24 120 °C 52 °C 8.00 A 6.5 - 16 s 2.50 A at 90 °C</p> <p style="text-align: center;">Run: ----- TPCo Process ----- 1009</p>																																																										
<p>Starting Relay : Sensata Code : -----</p> <p>Connection Type : Fast-on:--- Pick-up : ----- A Drop-out : ----- A</p> <p>Potential Relay : ELECTRICA Code : ----- Pick-up : --- V Drop-out : --- V</p> <p>Starting Relay - PTC : Sensata Code : ----- PTC-Resistance : --- Ohms Power Consumption of PTC : --- W</p> <p>Overload Protector : Sensata Code : ----- Connection Type : Fast-on:--- Disc Opening Temperature (+/-5°C) : --- °C Disc Closing Temperature (+/-9°C) : --- °C Time Check Current : --- A Time Check at 25°C : --- s Trip Current : --- A at --- °C</p> <p>Combo Module : Capacitor : Start: 47-56MFD 250VAC Connection Box : -----</p> <p>Note :</p>	<p style="text-align: center;">or</p> <p>COMPELA RP42XX</p> <p>Screw:--- Fast-on:38 Screw:--- 5.80 A 4.95 A</p> <p style="text-align: center;">or</p> <p>G.E. ----- ----- V ----- V</p> <p style="text-align: center;">or</p> <p>COMPELA ----- --- Ohms --- W</p> <p style="text-align: center;">or</p> <p>COMPELA T14526-XX</p> <p>Screw:--- Fast-on:23 Screw:24 120 °C 52 °C 8.00 A 6.5 - 16 s 2.50 A at 90 °C</p> <p style="text-align: center;">Run: ----- TPCo Process ----- 1009</p>																																																																

All information contained in this leaflet is subjected to change without previous notice

Printed on: Aug, 1 2011

Issued by: Gustavo Tadeu de Oliveira

Approved by: Cássio R. N. Maule

Revision:

Jun, 27 2011